

Sheet-current distribution in a dc SQUID washer probed by vortices

Dietmar Doenitz,¹ Matthias Ruoff,¹ Ernst Helmut Brandt,² John R. Clem,³ Reinhold Kleiner,¹ and Dieter Koelle^{1,*}

¹*Physikalisches Institut – Experimentalphysik II, Universität Tübingen,
Auf der Morgenstelle 14, 72076 Tübingen, Germany*

²*Max-Planck-Institut für Metallforschung, D-70506 Stuttgart, Germany*

³*Ames Laboratory - DOE and Department of Physics and Astronomy, Iowa State University, Ames Iowa 50011, USA*

(Dated: February 2, 2008)

We present a novel method, based on vortex imaging by low-temperature scanning electron microscopy (LTSEM), to directly image the sheet-current distribution in YBa₂Cu₃O₇ dc SQUID washers. We show that the LTSEM vortex signals are simply related to the scalar stream function describing the vortex-free circulating sheet-current distribution $\mathbf{J}$. Unlike previous inversion methods that infer the current distribution from the measured magnetic field, our method uses pinned vortices as local detectors for $\mathbf{J}$. Our experimental results are in very good agreement with numerical calculations of $\mathbf{J}$.

PACS numbers: 68.37.Hk, 74.25.Op, 74.78.-w, 85.25.Dq

Spatially resolved techniques can provide important insight into current flow, arrangement of vortices, flux pinning, and noise in superconductors and their mutual interactions. So far there has been only one method of imaging the current distribution in superconductors: The magnetic field distribution on top of a superconducting thin film is measured, e.g. by magneto-optics, from which the current distribution can then be calculated by inverting the Biot-Savart law[1].

In this paper we present a novel method to directly image the sheet-current distribution in a YBa₂Cu₃O₇ thin film. We use low-temperature scanning electron microscopy (LTSEM)[2, 3, 4, 5] to image vortices in dc SQUID washers[6, 7]. Most techniques for vortex imaging, such as Lorentz microscopy[8], scanning SQUID microscopy[9, 10], scanning Hall microscopy[11] or magneto-optics[12] rely on the detection of the stray magnetic field produced in close proximity to a vortex. In contrast, vortex imaging by LTSEM is different from those techniques, as it is based on the electron-beam-induced apparent displacement of a vortex, pinned at position $\mathbf{r}$ in the (x, y) -plane of a SQUID washer, which is detected as a *change* of stray magnetic flux $\Phi(\mathbf{r})$ coupled to the SQUID. Hence, the contrast of the LTSEM vortex signals directly senses $\nabla\Phi(\mathbf{r})$. Recently, Clem and Brandt[13] have shown that $\Phi(\mathbf{r})$ is proportional to the scalar stream function $G(\mathbf{r})$ that describes the circulating sheet-current density $\mathbf{J}(\mathbf{r})$ flowing in the vortex-free case at position $\mathbf{r}$ in the SQUID washer. In this paper we show that this relationship allows us to use the vortices as local detectors for $\mathbf{J}(\mathbf{r})$: At each position a vortex has been imaged, we can directly determine $\mathbf{J}(\mathbf{r})$ without complicated calculations.

In our experiments, we investigated several dc SQUID washers [see Fig. 1(a)] fabricated from epitaxially grown $d=80$ nm thick c -axis oriented YBa₂Cu₃O₇ (YBCO) thin

films. We will present an analysis of LTSEM data obtained from one representative device with washer size $120\,\mu\text{m} \times 305\,\mu\text{m}$, with a $100\,\mu\text{m}$ long and $4\,\mu\text{m}$ wide slit. The $1\,\mu\text{m}$ wide Josephson junctions are formed by a 24° symmetric grain boundary in the underlying SrTiO₃ substrate. For imaging by LTSEM, the YBCO SQUIDS are mounted on a magnetically shielded, liquid nitrogen cooled cryostage of an SEM [14] and read out by a standard flux-locked loop (FLL) with 3.125 kHz bias-current reversal to eliminate $1/f$ noise due to fluctuations in the critical current I_c of the Josephson junctions. All LTSEM images are obtained at $T = 77$ K after cooling the SQUID through T_c in a static magnetic field B_0 .

For the spatially resolved measurements, the electron beam is used as a local perturbation that induces an increase in temperature $\delta T(x - x_0, y - y_0)$ on the sample surface (in the x, y -plane) centered on the beam spot position (x_0, y_0) . At $T=77$ K the length scale for the spatial decay of the thermal perturbation is set by the beam-electron range $R \approx 0.5\,\mu\text{m}$ for a typical beam voltage $V_b = 10$ kV[4]. This gives a maximum increase in beam-induced temperature ΔT of a few K at (x_0, y_0) for typical beam currents I_b of a few nA. So-called $\delta\Phi(x_0, y_0)$ images are obtained by recording the e-beam-induced flux change $\delta\Phi$ in the SQUID as a function of the e-beam coordinates (x_0, y_0) . To improve the signal to noise ratio, we use a beam-blanking unit operating at typically 5 kHz, and the FLL output signal, i.e., the e-beam-induced flux change in the SQUID, is lock-in detected.

The mechanism of imaging of pinned vortices can be briefly described as follows: The e-beam-induced local increase in temperature produces a local increase in the Pearl length[15] $\Lambda = \lambda_L^2/d$, where λ_L is the temperature-dependent London penetration depth. Hence, the screening currents circulating around a pinned vortex are spatially extended due to e-beam irradiation. If the e-beam is scanned across a vortex, the vortex's magnetic-field distribution is distorted in the direction of the beam spot; i.e., the center of the distorted field distribution is displaced by δr , which depends upon the distance of the

*Electronic address: koelle@uni-tuebingen.de




FIG. 1: (a) SQUID washer design; dotted line indicates grain boundary. (b) $\delta\Phi$ image of washer SQUID. The arrow indicates the direction $\hat{d}$ of one of the vortex signals. Tick labels are in units of μm . (c) Line scan $\delta\Phi(x)$ along the dashed line shown in (b). The signal contrast C , i.e., the difference between maximum positive and negative signal from a single vortex, is indicated by the arrow.

beam spot from the vortex. This displacement changes the amount of stray magnetic flux $\Phi(\mathbf{r})$ in the negative z direction that a vortex at position $\mathbf{r}$ couples into the SQUID hole. Hence, scanning across a vortex induces a negative (positive) flux change $\delta\Phi$ in the SQUID if the vortex is moved away from (towards) the SQUID hole. Figure 1(b) shows an example of a $\delta\Phi$ image with vortices appearing as pairs of positive (bright) and negative (dark) signals.

Fig. 1(c) shows a linescan $\delta\Phi(x)$ of the vortex signal along the dashed line shown in Fig. 1(b). The difference between the maximum positive and negative signals from a single vortex defines the contrast C of a vortex in the $\delta\Phi$ image. The contrast C depends on the maximum vortex displacement Δr , which is independent of the vortex position, and on the gradient of the function $\Phi(\mathbf{r})$. Neglecting the (small) variation in $|\nabla\Phi(\mathbf{r})|$ within Δr , we can write

$$C = 2\Delta r |\nabla\Phi(\mathbf{r})|. \quad (1)$$

We define the direction $\hat{d}$ of a vortex signal [c.f. Fig. 1(b)] as the direction of a unit vector in the (x, y) -plane pointing from the maximum negative to maximum positive signal of the vortex. Hence, $\hat{d}$ is par-

allel to the gradient of $\Phi(\mathbf{r})$ and given as

$$\hat{d} \equiv \nabla\Phi(\mathbf{r})/|\nabla\Phi(\mathbf{r})|. \quad (2)$$

In the vortex-free case and for currents below the critical current of the Josephson junctions, the SQUID washer acts as a closed superconducting loop, which can carry a persistent supercurrent I , flowing clockwise or counterclockwise. The sheet-current density $\mathbf{J}(\mathbf{r})$ is divergence free; thus it can be written as

$$\mathbf{J}(\mathbf{r}) = I\hat{z} \times \nabla G(\mathbf{r}), \quad (3)$$

where $\hat{z}$ is the unit vector in the direction perpendicular to the film plane and $G(\mathbf{r})$ is a stream function. $G(\mathbf{r})$ depends on the Pearl length, the film thickness and the washer geometry; it can be chosen such that $G = 0$ on the outer edge and $G = 1$ on the inner edge of the SQUID[13]. This situation corresponds to the “trapped-flux case” (zero applied field, magnetic flux trapped in the hole and slit, which is bridged at the edge) shown in the upper left plot of Fig. 1 in Ref. 16.

While the function $\Phi(\mathbf{r})$ applies for the *vortex state* of the SQUID washer and the function $G(\mathbf{r})$ applies for the *vortex-free state*, Clem and Brandt used an energy argument to show that both functions are closely related[13] as

$$G(\mathbf{r}) = \frac{\Phi(\mathbf{r})}{\Phi_0}, \quad (4)$$

where $\Phi_0 = h/2e$ is the magnetic flux quantum. This equation holds as long as the current distribution in the vicinity of a vortex is not significantly altered by other vortices. This requirement is well fulfilled in our experiments since the applied fields are small (up to $40\mu\text{T}$) and thus the distance between the vortices is a few μm or more, well above $\Lambda \approx 0.5\mu\text{m}$ at $T = 77\text{K}$.

From equations (1)-(4) one obtains

$$\mathbf{J}(\mathbf{r}) = \frac{C}{\Phi_0} \cdot \frac{I}{2\Delta r} \cdot (\hat{z} \times \hat{d}), \quad (5)$$

i.e., $|\mathbf{J}(\mathbf{r})| \propto C$ and $\mathbf{J} \perp \hat{d}$. The magnitude of the vortex-free sheet-current density $\mathbf{J}$ at the position $\mathbf{r}$ of an imaged vortex is proportional to the contrast C of the LT-SEM signal given by that vortex, while the direction of $\mathbf{J}$ is perpendicular to the direction $\hat{d}$ of the vortex signal. These properties allow us to use the pinned vortices as local probes for the magnitude and direction of $\mathbf{J}$.

In order to check the validity of (5) we calculated the scalar stream function $G(\mathbf{r})$ and the vortex-free sheet-current density $\mathbf{J}(\mathbf{r})$ for the geometry of our SQUID washers, using the numerical simulation software package 3D-MLSI [17]. For the washer geometry in Fig. 1(a), $G(\mathbf{r})$ and $\mathbf{J}(\mathbf{r})$ are shown in Fig. 2(a) and (b), respectively.

In Fig. 3 we compare experimental data obtained from four $\delta\Phi$ images at different cooling fields (upper row)

with the numerically calculated sheet-current distribution $\mathbf{J}(\mathbf{r})$. In Fig. 3(e-h) (middle row) every vortex imaged by LTSEM is represented by a white arrow at the position of the imaged vortex. The direction of this arrow is perpendicular to $\hat{\mathbf{d}}$, and the length is proportional to the signal contrast C . From Eq. (5) it follows that the arrows should indicate the direction and magnitude of the normalized vortex-free sheet-current density $\mathbf{J}/I$. For comparison, Fig. 3(i-m) (bottom row) shows the results from numerical simulations; i.e., the black arrows represent the direction and magnitude of $\mathbf{J}(\mathbf{r})/I$. As shown in Fig. 3, the agreement between experimental data (middle row) and numerical simulation (bottom row) is very good. The rms deviations in magnitude and direction of the sheet-current density are given in Table I for four values of the cooling field. Since the proportionality constant between C and $\mathbf{J}/I$ contains Δr , which depends on experimental parameters such as e-beam power and sample temperature, we use Δr as a fitting parameter for each $\delta\Phi$ image [c.f. Table I] to obtain the best agreement between experimental and numerical simulation data. There seems to be a trend towards smaller values of Δr with increasing B_0 . The origin of this has not been clarified yet.

The deviations between experimental and simulation data for $\mathbf{J}/I$ can easily be explained by the difficulty to extract the direction and magnitude of the vortex signals exactly. Furthermore, vortices imaged close to the Josephson junctions yield a somewhat larger deviation in the direction of the sheet-current density as obtained from numerical simulations. During LTSEM imaging, shifts of the sample position up to a couple of μm in

TABLE I: Rms deviation between experimentally determined and numerically calculated sheet-current density $\mathbf{J}(\mathbf{r})$ and values for maximum beam-induced displacement Δr .

cooling field (μT)	rms deviation of magnitude	rms deviation of direction	Δr (nm)
5	16%	8.4°	103
10	20%	6.4°	85
15	19%	10.7°	82
40	26%	7.6°	79

both the x - and y -directions may occur. While such a shift along the x -direction can easily be corrected using the left and right (vertical) edges of the SQUID washer as a reference, a shift along the y -direction cannot be corrected by using the bottom washer edge as a reference, since we avoided directly hitting the Josephson junctions with the e-beam. In particular, for the largest cooling field $B_0 = 40 \mu\text{T}$, the analysis of the LTSEM data yields a significantly larger horizontal component for $|J|$ as compared to the numerically calculated current distribution [c.f. Fig. 3(f)]. Most likely, this deviation is due to a vertical shift which occurs during LTSEM imaging. Except for the signals close to the Josephson junctions we did not find a systematic deviation between experimental and numerical data.

In conclusion, we have shown that the relation between the vortex-generated flux Φ in a SQUID washer and the scalar stream function G allows us to use the vortices as local detectors for the sheet-current distribution $\mathbf{J}$ in the vortex-free case. This is a novel and more direct method of imaging circulating supercurrents that avoids complicated calculations. The experimental data obtained in magnetic fields up to $40 \mu\text{T}$ are in excellent agreement with numerical calculations of $\mathbf{J}$, confirming both the validity of our model describing the generation of the LTSEM vortex signals and the validity of the relationship derived by Clem and Brandt [13], even in the presence of many (up to 200) vortices in the SQUID washer.

We thank K. Barthel for fabricating the YBCO SQUIDS, John Clarke for providing detailed layouts of the Berkeley SQUID readout electronics and R. Straub for his support on LTSEM imaging. This work was supported by the ESF program VORTEX, the Landesforschungsschwerpunktprogramm Baden-Württemberg, Iowa State University of Science and Technology under Contract No. W-7405-ENG-82 with the U.S. Department of Energy, and the German Israeli Research Grant Agreement (GIF) No. G-705-50.14/01. D. D. gratefully acknowledges support from the Evangelisches Studienwerk e.V. Villigst.




FIG. 2: Numerical simulation for SQUID washer in the vortex-free case: (a) Scalar stream function G ; $G = 1$ (white) at the slit edge; $G = 0$ (black) at the outer edge. (b) Streamlines, showing the current distribution in the SQUID washer.




FIG. 3: Upper row: LTSEM $\delta\Phi$ images for different cooling fields B_0 . Middle row: Magnitude and direction of sheet-current density calculated from the corresponding $\delta\Phi$ images (white arrows). Bottom row: Magnitude and direction of sheet-current density calculated by numerical simulation of $\mathbf{J}(\mathbf{r})$ (black arrows). Tick labels are in units of μm .

-
- [1] C. Jooss, J. Albrecht, H. Kuhn, S. Leonhardt, and H. Kronmüller, Rep. Prog. Phys. **65**, 651 (2002).
 - [2] J. R. Clem and R. P. Huebener, J. Appl. Phys. **51**, 2764 (1980).
 - [3] R. P. Huebener, Rep. Prog. Phys. **47**, 175 (1984).
 - [4] R. Gross and D. Koelle, Rep. Prog. Phys. **57**, 651 (1994).
 - [5] T. Doderer, Int. J. Mod. Phys. B **11**, 1979 (1997).
 - [6] R. Straub, S. Keil, R. Kleiner, and D. Koelle, Appl. Phys. Lett. **78**, 3645 (2001).
 - [7] D. Doenitz, R. Straub, R. Kleiner, and D. Koelle, Appl. Phys. Lett. **85**, 5938 (2004).
 - [8] A. Tonomura, H. Kasai, O. Kamimura, T. Matsuda, K. Harada, Y. Nakayama, J. Shimoyama, K. Kishio, T. Hanaguri, K. Kitazawa, et al., Nature **412**, 620 (2001).
 - [9] F. Tafuri, J. R. Kirtley, P. G. Medaglia, P. Orgiani, and G. Balestrino, Phys. Rev. Lett. **92**, 157006 (2004).
 - [10] J. R. Kirtley, C. C. Tsuei, M. Rupp, J. Z. Sun, L. S. Yu-Jahnes, A. Gupta, M. B. Ketchen, K. A. Moler, and M. Bhushan, Phys. Rev. Lett. **76**, 1336 (1996).
 - [11] A. N. Grigorenko, S. J. Bending, M. J. VanBael, M. Lange, V. V. Moshchalkov, H. Fangohr, and P. A. J. de Groot, Phys. Rev. Lett. **90**, 237001 (2003).
 - [12] P. E. Goa, H. Hauglin, M. Baziljevich, E. Il'yashenko, P. L. Gammel, and T. H. Johansen, Supercond. Sci. Technol. **14**, 729 (2001).
 - [13] J. R. Clem and E. H. Brandt, cond-mat/0507524 (2005). Our definitions of $\mathbf{J}$, G , and Φ differ from those of $\mathbf{J}_d$, G_d , and Φ_v in Ref. 13. They are related via $\mathbf{J} = -\mathbf{J}_d$, $G = 1 - G_d$, and $\Phi = \Phi_0 - \Phi_v$.
 - [14] R. Gerber, T. Nissel, H.-G. Wener, A. Willmann, R. Huebener, D. Koelle, and R. Gross, Cryogenics **37**, 21 (1997).
 - [15] J. Pearl, Appl. Phys. Lett. **5**, 65 (1964). The spatial dependence of the supercurrent and magnetic-field distributions is governed by the Pearl length when the film thickness d is less than λ_L , which is the case in the present experiments.
 - [16] E. H. Brandt, Phys. Rev. B **72**, 024529 (2005).
 - [17] M. Khapaev, M. Kupriyanov, E. Goldobin, and M. Siegel, Supercond. Sci. Tech. **16**, 24 (2003).